


|   |                                    |  |          |
|---|------------------------------------|--|----------|
|  | <b>GENERAL SPECIFICATIONS</b>      | 50-09-<br>073_SPG_SigFox_Dual_Input_State_Sensor_E<br>N.docx |          |
|   | ICT SigFox Dual Input State Sensor | Rev: 1   | Page 1/8 |

## GENERAL SPECIFICATIONS

### ICT SigFox Dual Input State Sensor

#### Document revision history


| DATE       | REVISION | OBJECT  | Author |
|------------|----------|---|--------|
| 08/01/2017 | 0        | Creation  | PLG    |
| 07/09/2017 | 1        | Precision regarding temperature conditions for the battery's theoretical service life | MC     |

|                 | WRITTEN BY       | APPROVED BY       |
|-----------------|------------------|-------------------|
| <b>NAME</b>     | Patrice LE GARFF | Stéphane DUTERTRE |
| <b>POSITION</b> | RPJ              | RBE               |

**CAUTION:** unless otherwise stated (below), this is an uncontrolled copy of an computer document. Refer to the nke Document Manager software for more information.

nke ☎ (33).02.97.36.10.12 Fax (33).02.97.36.55.17.. ..<http://www.nke.fr>

Model SPG.dot Rev1 of 14/12/04

|   |                                    |  |          |
|---|------------------------------------|--|----------|
|  | <b>GENERAL SPECIFICATIONS</b>      | 50-09-<br>073_SPG_SigFox_Dual_Input_State_Sensor_E<br>N.docx |          |
|   | ICT SigFox Dual Input State Sensor | Rev: 1   | Page 2/8 |


## TABLE OF CONTENTS

|   |          |
|---|----------|
| <b>1. OBJECT OF THE DOCUMENT</b>                                  | <b>3</b> |
| <b>2. APPLICABLE DOCUMENTS - REFERENCE DOCUMENTS</b>              | <b>3</b> |
| <b>3. DEFINITIONS - TERMINOLOGY</b>                               | <b>3</b> |
| <b>4. BACKGROUND AND OBJECTIVES OF THE STUDY</b>                  | <b>3</b> |
| <b>5. GENERAL STRUCTURE OF THE PRODUCT</b>                        | <b>3</b> |
| 5.1 MECHANICAL PRESENTATION                                       | 3        |
| 5.2 POWER SUPPLY  | 4        |
| 5.3 INFORMATION FRAME AND POWER SUPPLY SELF-TEST                  | 4        |
| 5.4 CONFIGURATION SETTINGS FOR THE SIGFOX DUAL INPUT STATE SENSOR | 5        |
| 5.5 ON-BOARD INPUTS   | 5        |
| 5.6 CHANGE OF STATE DETECTION                                     | 5        |
| 5.7 MICROCONTROLLER   | 5        |
| 5.8 NFC TAG   | 5        |
| <b>6. FUNCTIONS OF THE PRODUCT IN INSTALLATION AND USE</b>        | <b>5</b> |
| 6.1 OPERATION AND COMMUNICATION                                   | 5        |
| 6.2 INPUT STATE DATA  | 6        |
| 6.3 ALARM DATA  | 6        |
| <b>7. MANUFACTURABILITY</b>                                       | <b>6</b> |
| 7.1 TESTABILITY   | 6        |
| 7.2 IDENTIFICATION-TRACEABILITY                                   | 6        |
| 7.3 PACKAGING   | 7        |
| <b>8. MAINTAINABILITY</b>   | <b>7</b> |
| <b>9. DESIGN CONSTRAINTS</b>                                      | <b>7</b> |
| 9.1 OPERATING TEMPERATURE   | 7        |
| 9.2 STORAGE TEMPERATURE   | 7        |
| 9.3 POWER SUPPLIES  | 7        |
| 9.4 TIGHTNESS - IP RATING   | 7        |
| 9.5 AUTONOMY  | 7        |
| 9.6 MECHANICAL STRESS - SHOCKS - VIBRATIONS                       | 7        |
| <b>10. NORMATIVE REQUIREMENTS</b>                                 | <b>7</b> |
| 10.1 ELECTROMAGNETIC COMPATIBILITY                                | 7        |
| 10.2 ELECTRICAL SAFETY  | 7        |
| 10.3 STANDARDS AND REGULATIONS SPECIFIC TO THE BUSINESS SEGMENT   | 7        |
| <b>11. MARKETING SPECIFICATIONS</b>                               | <b>8</b> |
| 11.1 PRODUCT SERVICE LIFE   | 8        |
| 11.2 PRICING STRUCTURE  | 8        |
| 11.3 GUARANTEE  | 8        |
| 11.4 MAINTENANCE  | 8        |
| 11.5 PRODUCT DOCUMENTATION REQUIREMENTS                           | 8        |

**CAUTION: unless otherwise stated (below), this is an uncontrolled copy of an computer document. Refer to the nke Document Manager software for more information.**

**nke** ☎ (33).02.97.36.10.12 Fax (33).02.97.36.55.17.. ..<http://www.nke.fr>

Model SPG.dot Rev1 of 14/12/04

|   |                                    |  |          |
|---|------------------------------------|--|----------|
|  | <b>GENERAL SPECIFICATIONS</b>      | 50-09-<br>073_SPG_SigFox_Dual_Input_State_Sensor_E<br>N.docx |          |
|   | ICT SigFox Dual Input State Sensor | Rev: 1   | Page 3/8 |

## 1. OBJECT OF THE DOCUMENT

Describe the operation and technical characteristics of the product "**SigFox dual input state sensor**" (state monitoring over 2 on/off inputs and SigFox radio technology).

## 2. APPLICABLE DOCUMENTS - REFERENCE DOCUMENTS

- Detailed software specifications - SigFox sensors data exchanges:  
[50-09 SigFox SPDL Sensor.pdf](#)

## 3. DEFINITIONS - TERMINOLOGY

**SigFox**: the SigFox technology provides low bandwidth, long range, secured UNB (Ultra Narrow Band) radio communication with very low energy consumption. The star network covers an end-to-end transmission, from the equipment to the information system.



## 4. BACKGROUND AND OBJECTIVES OF THE STUDY

The SigFox dual input state sensor has been developed based on new electronics that incorporate the SigFox technology.

Important: the sensor must be placed under coverage of the SigFox public network.

This sensor includes 2 distinct on/off inputs designed to receive the state of 2 isolated dry contacts. At each change of state of one of the two inputs, the states of these inputs are transmitted on the SigFox network.

Important: the costs associated with network access (subscription and volume) are borne by the customer.

## 5. GENERAL STRUCTURE OF THE PRODUCT

### 5.1 Mechanical presentation

The SigFox dual input state sensor board is housed in a grey ABS enclosure.

The sensor must be sheltered so as not to be subjected to excessive external stresses or excessively fast changes in ambient conditions (sun radiation, wind, rainfall, etc.) that may be detrimental to the quality of the measurements.

It must be placed at least 1 metre away from any metal element that can constitute a ground plane that significantly attenuates the radio signal.


When the sensor is installed indoors, extra attention must be paid to the SigFox network coverage, which is greatly reduced in this case.

In order to be installed outdoors, the sensor enclosure is that of the SigFox Pulse S0 model.

**CAUTION: unless otherwise stated (below), this is an uncontrolled copy of a computer document. Refer to the nke Document Manager software for more information.**

nke ☎ (33).02.97.36.10.12 Fax (33).02.97.36.55.17.. ..http://www.nke.fr

Model SPG.dot Rev1 of 14/12/04

|   |                                    |  |          |
|---|------------------------------------|--|----------|
|  | <b>GENERAL SPECIFICATIONS</b>      | 50-09-<br>073_SPG_SigFox_Dual_Input_State_Sensor_E<br>N.docx |          |
|   | ICT SigFox Dual Input State Sensor | Rev: 1   | Page 4/8 |



The enclosure is disassembled by unscrewing the fixing screws located on the front shell.

The sensor incorporates a SigFox radio transceiver associated with an antenna located inside the enclosure. Two cable glands allow the passage of cables (two 2-conductor cables) intended to be connected to the board.

**Important:** for cables intended to be connected to the dual input state sensor board, we recommend using moulded (not simply sheathed) circular cables to avoid any detrimental effect to the tightness of the product. Cables are not supplied with the products.

The minimum/maximum outside diameters allowed for the cable are 2 / 6.5 mm.

The electrical connection is made on spring-type terminal blocks with 3.5mm pitch using 2-conductor cables (max. length: 5 metres).

The position of the points is marked on the copper elements of the board.

The external dimensions are approximately 84 x 82 x 55 mm.

The IP55 enclosure complies with flammability standard UL94-V0 HB (no flame propagation).

There is no provision for tearing detection.

## 5.2 Power supply

The SigFox dual input state sensor board is powered by a lithium battery. The electronics are designed in such a way as to obtain a very low standby current that allows for a low lithium battery capacity.

The theoretical service life of the sensor is 12 years based on 3 changes of state per day for each of the 2 inputs.

The battery is replaced at the factory.

[This theoretical lifetime of the battery is valid for the operating temperature range of +10 °C to +25 °C.](#)

## 5.3 Information frame and power supply self-test

Sensor information frames are sent during the period of radio transmission of these information frames set in the product configuration but also 5 minutes after the sensor is activated, and at every change in software or product configuration. The information sent in these frames are: the battery voltage measurement, the number of radio transmissions, the software and product configuration version and subversion.


Indeed, the board measures the supply voltage of its battery and sends the measurement during the period of radio transmission of sensor information frames set in the product configuration. The sensor is capable of detecting a low battery information. If the voltage drops below a minimum threshold, an alarm is sent to the network after the data has been transmitted.

The number of radio transmissions corresponds to the number of radio transmissions that the sensor has made since leaving the factory.

**CAUTION:** unless otherwise stated (below), this is an uncontrolled copy of an computer document. Refer to the nke Document Manager software for more information.

nke ☎ (33).02.97.36.10.12 Fax (33).02.97.36.55.17.. ..<http://www.nke.fr>

Model SPG.dot Rev1 of 14/12/04

|   |                                    |  |          |
|---|------------------------------------|--|----------|
|  | <b>GENERAL SPECIFICATIONS</b>      | 50-09-<br>073_SPG_SigFox_Dual_Input_State_Sensor_E<br>N.docx |          |
|   | ICT SigFox Dual Input State Sensor | Rev: 1   | Page 5/8 |

The software and product configuration versions and subversions have the following formats:

- Software: 01.00 (version: 01 and subversion: 00)
- Configuration: 02.05 (version: 02 and subversion: 05)

#### **5.4 Configuration settings for the SigFox dual input state sensor**

The sensor is supplied with factory settings, defined at the time of the order:

- **Interval of sensor information frames** between two radio transmissions (measured battery voltage, number of radio transmissions, software and configuration version and subversion): 0 to 30 days, in 1 day increments ("0": deactivation of sensor information frame transmission)
- **Alarm threshold: minimum battery level** for threshold overrun alarm (from 1 to 36 1/10V, i.e. from 0.1 V to 3.6 V)

Later versions will allow these configuration settings to be updated directly on the sensor using a micro SD card (connector present on the board) on which a configuration file that specifies the new values of these settings will be loaded.

The embedded software will also be updated locally using a micro SD card.

The settings of the sensor configuration file are specified in the document "[50-09\\_SigFox\\_SPDL\\_Sensor.pdf](#)".

#### **5.5 On-board inputs**

The sensor includes 2 distinct inputs designed to receive the state of 2 isolated dry contacts (level S0, normally open i.e. the signal is grounded in the activated state, contact compatible with very low polarisation current).

#### **5.6 Change of state detection**

At regular intervals, the sensor wakes up to check the state of each input. If one of them varies, the two states are immediately transmitted over the SigFox network as an alarm, after which the sensor is placed in standby mode.

The microcontroller manages its consumption optimally according to its parameters.

#### **5.7 Microcontroller**

A Flash memory inside the microcontroller supports:

- the software: the sensor is supplied with the current version of the software (later versions will allow local updates via a micro SD card).
- the configuration settings for the operating profile (later versions will allow local updates via a micro SD card).

#### **5.8 NFC tag**

An NFC tag attached to the sensors (inside the enclosure) includes a product type, as well as a unique internal identification code in order to simplify any intervention by the installer, who will retrieve this information by "tagging" the product.

## **6. FUNCTIONS OF THE PRODUCT IN INSTALLATION AND USE**


### **6.1 Operation and communication**

A magnetic sensor (reed switch) activated by a magnet and an embedded confirmation buzzer allow the sensor to be taken out of storage mode and to initiate communication with the network (start "alarm").

**CAUTION: unless otherwise stated (below), this is an uncontrolled copy of a computer document. Refer to the nke Document Manager software for more information.**

**nke** ☎ (33).02.97.36.10.12 Fax (33).02.97.36.55.17.. ..<http://www.nke.fr>

Model SPG.dot Rev1 of 14/12/04

|   |                                    |  |          |
|---|------------------------------------|--|----------|
|  | <b>GENERAL SPECIFICATIONS</b>      | 50-09-<br>073_SPG_SigFox_Dual_Input_State_Sensor_E<br>N.docx |          |
|   | ICT SigFox Dual Input State Sensor | Rev: 1   | Page 6/8 |

Similarly, the system can be stopped by reactivating the magnetic sensor (reed switch). When the sensor is stopped, it also transmits a stop "alarm".

With every change of state of one of the inputs, the sensor transmits the state of both inputs.

"Low battery" alerts are sent during the period of radio transmission of information that follows their detection, if this function is activated.

## 6.2 Input state data

The state data structure of the sensor is specified in the document "[50-09\\_SigFox\\_SPDL\\_Sensor.pdf](#)".

Each input can be either open or closed.

Changes of state are transmitted as an alarm.

Bounce filtering is implemented over a period of 5 seconds to eliminate interference conditions.

## 6.3 Alarm data

Important: between two measurements, the sensor goes into standby mode. No alarm shall be detected (e.g. low battery voltage). It is not until the next measurement that a possible alarm will be detected and sent immediately.

The different types of alarms are:

- Product activation/deactivation alarms
- Power supply alarms (low battery)
- State of inputs upon a change of state of one of the two inputs

## 7. MANUFACTURABILITY

In order to limit production costs, the electronic boards will have to follow a conventional manufacturing process involving a mix of SMD and through-hole components wave soldered onto FR4 epoxy printed circuit board with metallised holes.

In compliance with EMC standards and despite the additional cost generated, a 4-layer CAD with the most significant ground plane possible shall be favoured. The finish of printed circuit boards shall comply with the latest Lead Free / RoHS specifications.

### 7.1 Testability

An in situ test (or one similar in performance) is carried out at 100% once the components are inserted. A functional check is performed by a test software embedded in each SigFox dual input state sensor and specific tooling.

Mounting pads for test probes shall be arranged on the traces of strategic signals. A PC software shall be used for programming the microcontroller and shall use a plug-in connector.


### 7.2 Identification-Traceability

Products are identified individually. Each board is programmed with a unique serial number. Each sensor bears a unique internal identification code visible on the product identification label.


This label allows traceability and indicates:

- the NKE product group code (50-09-073-xxx)
- a unique NKE code for determining the manufacturing order (MO) number and the product number in the MO
- the serial number

**CAUTION: unless otherwise stated (below), this is an uncontrolled copy of an computer document. Refer to the nke Document Manager software for more information.**

nke  (33).02.97.36.10.12 Fax (33).02.97.36.55.17.. ..<http://www.nke.fr>

Model SPG.dot Rev1 of 14/12/04

|   |                                    |  |          |
|---|------------------------------------|--|----------|
|  | <b>GENERAL SPECIFICATIONS</b>      | 50-09-<br>073_SPG_SigFox_Dual_Input_State_Sensor_E<br>N.docx |          |
|   | ICT SigFox Dual Input State Sensor | Rev: 1   | Page 7/8 |

### 7.3 Packaging

Each board is delivered mounted in an enclosure.

When shipped, the SigFox dual input state sensors are grouped in batches, in a cardboard box capable of withstanding transport constraints.

## 8. MAINTAINABILITY

There is no provision for preventive maintenance operations.

The product must be returned to the factory to carry out after-sales service or to replace the battery.

## 9. DESIGN CONSTRAINTS

### 9.1 Operating temperature

Operating range comprised between -20°C and +50°C.

### 9.2 Storage temperature

Storage range comprised between -10°C and +30°C (limited by the battery).

### 9.3 Power supplies

Power is provided by a lithium battery.

### 9.4 Tightness - IP rating

IP55.

### 9.5 Autonomy

See paragraph above.

### 9.6 Mechanical stress - shocks - vibrations

Measures are taken during wiring to prevent the tool used (e.g. screwdriver) from tearing off a component if it slips.

## 10. NORMATIVE REQUIREMENTS

### 10.1 Electromagnetic compatibility

For CE marking purposes, products comply with the general EMC regulations for electronics. NKE takes care of the testing necessary to ensure the compatibility of its products

The selected radio component complies with standards EN 300-220 / EN 301-489.

### 10.2 Electrical Safety

N/A

### 10.3 Standards and regulations specific to the business segment


NF EN-60335-1

Products are designed and manufactured in accordance with Directive 2002/96/EC on Waste Electrical and Electronic Equipment and Directive 2002/95/EC on the Restriction of Hazardous Substances (RoHS).

**CAUTION: unless otherwise stated (below), this is an uncontrolled copy of a computer document. Refer to the nke Document Manager software for more information.**

nke ☎ (33).02.97.36.10.12 Fax (33).02.97.36.55.17.. ..http://www.nke.fr

Model SPG.dot Rev1 of 14/12/04

|   |                                    |  |          |
|---|------------------------------------|--|----------|
|  | <b>GENERAL SPECIFICATIONS</b>      | 50-09-<br>073_SPG_SigFox_Dual_Input_State_Sensor_E<br>N.docx |          |
|   | ICT SigFox Dual Input State Sensor | Rev: 1   | Page 8/8 |

## **11. MARKETING SPECIFICATIONS**

### **11.1 Product service life**

7 years minimum

### **11.2 Pricing structure**

The applicable pricing conditions are those set out in the applicable commercial offerings.

### **11.3 Guarantee**

Products are guaranteed 24 months from the date of delivery by NKE, subject to implementation in accordance with the rules set out in the technical specifications.

### **11.4 Maintenance**

N/A. Except for battery replacement, which requires the product to be returned to the factory.

### **11.5 Product documentation requirements**

Customer's responsibility.

**CAUTION: unless otherwise stated (below), this is an uncontrolled copy of an computer document. Refer to the nke Document Manager software for more information.**

**nke** ☎ (33).02.97.36.10.12 Fax (33).02.97.36.55.17.. ..<http://www.nke.fr>

Model SPG.dot Rev1 of 14/12/04